



# Honeywell

## L5000ADT WIRELESS CONTROL PANEL



Part of Honeywell's family of self-contained wireless controls, ADT's dynamic L5000ADT has a bright, full-color touchscreen that simplifies security system operation. Whether arming or disarming the system, bypassing zones or leaving messages or reminders for family members, the graphics and intuitive, menu-driven prompts make operation crystal clear—reducing end user training time and false alarms.

L5000ADT is ideal for new installations and upgrades—letting security dealers provide next-generation interactive security as well as RMR-generating services like ADT Pulse Remote Services and two-way voice over GSM. These communications options give dealers the flexibility they need to service all of their customers, whether they rely on mobile phones, VoIP or POTS lines.

L5000ADT supports all Honeywell 5800 Series wireless devices, including the 5828 and 5828V wireless keypads.

## FEATURES

### System Features

- 4.7 inch color graphic touchscreen
  - Resolution 470 x 256 pixels
  - 16.7 million colors
  - Intuitive easy-to-use touchscreen interface
  - Easy to understand icons
  - Menu driven navigation
  - Quick accurate programming
  - Four dedicated keys for everyday functions
- Works with ADT Pulse Tier 1\* (Remote)
- Voice announcement of system and zone status
- Family message center (for user recorded messages)
- Voice chime by zone
- Automatic stay arming
- Remote phone control
- 16 programmable reminders

- “Follow me” reminder and system announcements; users can be notified by phone of reminders and system events. Supports two end-user phone numbers.
- 16 user codes (Installer, Master, Babysitter, Duress, 14 Secondary)
- Three panic functions
- Wall or desk mount
- Viewable event log stores up to 128 events
- Case tamper
- Exit error feature (detects difference between an actual alarm and exit alarm caused by leaving a door open after the exit delay expires)
- RF jam detection
- Quick Exit feature enables users to leave the premises for a brief time without disarming system
- Hinged cover for easy installation
- Real-time clock display

### Zones and Devices

- One hardwired zone
- Up to 64 total wireless zones (5800 Series Transmitters)
- Supports wireless bidirectional keypads
- 4GVLP5-ADT GSM radio option
- Programmable trigger output

\*Requires 4GVLP5-ADT GSM Radio

# L5000ADT

## WIRELESS CONTROL PANEL

### FEATURES (continued)

#### Communication

- ADEMCO® Contact ID Reporting (four or 10 digit account numbers)
- GSM cellular central station communication with 4GVLP5-ADT
- GSM radio signal strength display
- Two-way voice communication over telephone line or GSM with 4GVLP5-ADT

#### Alarm Output

- Built-in 85 dB sounder with voice siren
- Steady output for burglary/panic
- Temporal pulse output for fire and carbon monoxide alarms

#### Programming

- Intuitive programming interface reduces time and mistakes
- Programming options selected from allowable list
- Contextual options, defaults and pre-fills for faster set-up
- Can be uploaded, downloaded or controlled using Compass Downloader software

#### System Power

- Primary power: plug-in power supply, 110VAC to 9VDC, 2.7A output 300-04705V1 or 300-04065V1 (300-04063V1 in Canada)
- Four or 24-hour backup battery: rechargeable nickel-metal hydride battery pack rated at 7.2Vdc.
- Operating temperature: 32°F – 122°F (0°C – 50°C)

#### Dimensions

6.1" H x 8.5" W x 1.8" D (15.5cm H x 21.5cm W x 4.5cm D)

### ORDERING

<b>L5000ADTLB</b>	L5000ADTLB less battery Touchscreen Color Graphic Wireless Self-Contained Security System
<b>L5000ADTCNLB</b>	L5000ADTCN less battery Touchscreen Color Graphic Wireless Self-Contained Security System (Canada)
<b>L5000DM</b>	LYNX Desk Mount Accessory
<b>4GVLP5-ADT</b>	GSM Communicator L5000ADT
<b>LT-CABLE</b>	LYNX 5000 Family Power Cord
<b>LYNXRCHKIT-SHA</b>	24-Hour Backup Battery for L5000 and 4GVLP5-ADT Radio
<b>LYNXRCHKIT-HC</b>	24-Hour Backup Battery for L5000ADT

#### For more information:

[www.honeywell.com/security](http://www.honeywell.com/security)

#### Automation and Control Solutions

Honeywell Security Products Americas  
2 Corporate Center Dr. Suite 100  
P.O. Box 9040  
Melville, NY 11747  
1.800.467.5875  
[www.honeywell.com](http://www.honeywell.com)



# Honeywell